

KENWOOD

Listen to the Future



TK-5410

700/800MHz FM & P25 Digital Portable Radio



GENERAL FEATURES

- 3 Watt
- 100 Zones / 1024 Channels
- 12-Key Keypad Model
- Personality Lists
- Backlit Dot Matrix LCD
- 16 Character Alphanumeric Aliases
- 3-Digit Sub-Display
- Function / Status LCD Icons
- RSSI Indicator
- Transmit / Busy / Call Alert / Warn LED
- On/Off Volume Knob
- 16-Position Selector Knob
- 2-Position PF Lever Switch
- 3-Position PF Concentric Switch
- 4 Front Menu-Driven PF Keys
- 3 Side PF Keys
- Orange Emergency / AUX Key
- Zone / Ch Voice Announce
- VOX Ready
- Emergency Features
- Tactical Group
- Battery Level
- Transceiver Password
- Date & 12/24 Hour Time Clock
- Windows® Programming & Tuning¹
- Windows® Firmware Uploading¹
- Voice Guide & Storage (option)*
- Weather-Sealed Accessory Connector
- MIL-STD-810 C/D/E/F
- IP54/55 Water & Dust Protection
- Immersion (IP66/67/68) Option
- Intrinsically Safe Option*

SCAN TYPES (FM & P25)

- Single Zone/Multi-Zone Scan
- Scan Lists
- Conventional Scan
- Limited Talk Group Scan*
- Priority Monitor Scan
- Dual Priority Scan

FM

- QT / DQT
- Operator Selectable Tone²
- DTMF Encode
- Companded Audio
- NPSPAC Channels

P25 DIGITAL

- P25 Digital Conventional
- P25 Digital Trunking
- AMBE+2™ Enhanced VOCODER
- Talk Group ID Lists
- Individual ID Lists
- Caller ID Display
- Remote Monitor / Check, Radio Inhibit
- Encryption Key Zeroize & Retention
- DES Encryption Module
- AES & DES Encryption Module
- KPG-36AM Radio Program/Soft-Key Loader Cable
- KPG-93 KVL Device Key Loader Cable³
- P25 GPS Location*
- P25 OTAR Option*

*Future availability



Two models available:

K2: 16-Character LCD, 4 Menu-driven PF Keys

K3: 16-Character LCD, 4 Menu-driven PF Keys, 12-Key DTMF/PF Keypad

(Not actual size)

